#### **Product datasheet**

#### **BAZZ AIR**



# BZ1SF200AOSYRGBXB



#### BAZZ AIR SYM 2M RGBW BK.

#### Description:


Outdoor luminaire model BAZZ AIR SYM 2M RGBW BK., LAMP brand. Made of matt black anodized extruded aluminium and transparent polycarbonate diffuser. Model for RGBW LED and control gear included. With a symmetric metallised mat polycarbonate reflector. IP6 7, IK10 protection rating. Insulation class I. It allows swivels between 0° and 90°.

Finish: Anodized matte black

**Dimensions:** 2.001 x 75 x 88 mm **Weight:** 8.960 g

IEE: A+

Installation: Surface



#### **TECHNICAL SPECIFICATIONS:**

Light output: 1.484 lm 

•K: RGBW

Plum: 57W

Efficacy: 26 lm/w Alimentación: 110-240V 50/60Hz

Type: MID POWER AVAGO

Power: 51W





















Gear:





Electronic







### **CUSTOM MADE OPTIONS:**

Tel. +34937366800

LAMP reserves the right to change the technical specifications of their products. These changes will allow the continual improvement of the products and will also ensure the conformity to current legal changes. Updated information is always available in our website www.lamp.es.

07-04-2021 Pág. 1/3


### **BAZZ AIR**





BZ1SF200AOSYRGBXB

### BAZZ AIR SYM 2M RGBW BK.

#### **PHOTOMETRIC DATA:**







-				
	H (m)	D (m)	Emax	Emed
	1	1,50	686	468
	2	2,99	172	117
	3	4,49	76	52
	4	5,99	43	29

#### **Product datasheet**

#### **BAZZ AIR**



## ACCESORIES:

## Assembly



Product code: Description:

BZJO BAZZ AIR ACC. CONT LINE JOINT

#### **ACCESORIES:**

### Suspension



Product code: Description:

SUWIDE1000G ACC. QUICK STEEL CABLE 1M NK.
SUWIDE4000G ACC. QUICK STEEL CABLE 4M NK.

#### **ACCESORIES:**

## Support



Product code: Description:

ARROEX40G ACC. ADJ EXTEN WALL ARM GR.



Product code: Description:

BZSFCL1 BAZZ AIR ACC. Ø120 POLE 1CLAMP GR.
BZSFCL2 BAZZ AIR ACC. Ø120 POLE 2CLAMP GR.

#### **ACCESORIES:**

## Adjustment and control



Product code: Description:

DMXEXT ACC. DMX CONTROLLER



Product code:

DMXUSB ACC. DMX/RDM CHANNEL ADDRESSING USB

Description: