#### HANCE DOWNLIGHT




#### HD2SR30MF840NW



#### HANCE G2 DOWN SEMIREC 3000 NW MFL WH

#### Description:

LAMP multidirectional semi-recessed downlight HANCE G2 DOWN SEMIREC 3000. Allowing 355° rotation and tilting up to 85°. Body and frame made of die-cast aluminium for proper thermal management. Black polycarbonate injection moulded anti-glare ring. 25° middle flood reflector. LED COB, 4000K and CRI80. Electronic ON OFF control gear included. IP20, IK07 ratings. Insulation Class II. LED life time: 72.000 L80B10 (Ta=25°C). Available finishes: Textured white and textured black.



Finish: Texturised white RAL 9010

Installation: Recessed

#### **TECHNICAL SPECIFICATIONS:**

Light output: 3.549 lm °K: 4000 Plum: 28,3W CRI: 80 Efficacy: 125,4 lm/w R9: 64 UGR: <19 MacAdam: 3

Type: COB Power Supply: 220-240V 50/60Hz

LED Lifetime: 72.000 L80B10 (Ta=25°C) Gear: Electronic

25W Power:

#### Light output tolerance +/- 10%





























# **CUSTOM MADE OPTIONS:**









Data according to regulations 2019/2020/EU and 2019/2015/EU

















#### HANCE DOWNLIGHT





HD2SR30MF840NW


## HANCE G2 DOWN SEMIREC 3000 NW MFL WH

#### **PHOTOMETRIC DATA:**

HD2SR30MF840NW
η = 100%
Imax = 3926 cd/klm
UTE:
CIE: 101 100 100 100 100







Data according to regulations 2019/2020/EU and 2019/2015/EU

## HANCE DOWNLIGHT



# ACCESORIES:

## Optical



Product code:

HS2HO75



Product code:

HANCE G2 3000/4000 ACC. HONEYCOMB GRILLE HS2RI90C



HANCE G2 3000/4000 ACC. RING DECO CO.



Product code:

HS2RI90M



HANCE G2 3000/4000 ACC. RING DECO MET.

Product code:

HS2RI90W

Description:

HANCE G2 3000/4000 ACC. RING DECO WH.



Product code:

Description:

Description:

HS2TR75 HANCE G2 3000/4000 ACC. DIF TRANS